



Τα “CONTROLLERS” καθιστούν δυνατή την αξιοποίηση της τεχνολογίας LED στο μέγιστο. Ανακαλύψτε την λύση που ταιριάζει στον δικό σας χώρο και απλά στηριχθείτε στην πληρότητα και τον επαγγελματισμό μας.

Όλος ο απαραίτητος εξοπλισμός και η τεχνική υποστήριξη για τον φωτισμό σας, είναι διαθέσιμα από την BARISLIGHT®.

“CONTROLLERS” help you exploit LED technology to the fullest. Rely on our services and we can find together the solution that best fits your area. BARISLIGHT® provides you with all the necessary equipment and technical support of your lighting ideas and applications.

**code** Ω1011003-001

**product name** MINI ZIGBEE PRO 5in1 SMART LED CONTROLLER max 144W

### Specifications

**frequency** Adjustable between 600 and 8000 Hz

**Input Voltage** DC5-24V

**total power** 144 W Max

**output current / Channel** 3A Max

**total output current** 6A Max

**protection rate** IP20

**operating temperature** -20 ~ 45°C

Common Anode

Constant Voltage

Συνδιάζεται με / Pairing with **REMOTE CONTROL 2.4G RF 6-ZONE DC 3V** (code: Ω1011003-002)

**dimensions** 70x36x10mm LxWxH

### Notes on compatibility

The controller is compatible with most ZigBee ZLL and ZigBee 3.0 gateways.

It was tested with Philips Hue®, Osram Lighify®, Amazon Echo Plus.

Cable cross section for input and output 0.205-0.823mm<sup>2</sup> or AWG24-18.

- “Mini” control unit for ZigBee 3.0 / MiLight lighting control.
- 5in1 - single color, CCT, RGB, RGBW, RGB CCT lighting
- Voltages 5VDC / 12VDC / 24VDC up to 144 watts of power
- Frequency adjustable between 600 and 8000 Hz
- Switch-on behavior can be determined (*fixed or last setting*)

